

# FLOS

F6602004 Silver

## Taccia

Designed by Achille and Pier Giacomo Castiglioni, 1962


28W - 2700K



Table lamp providing indirect and reflected light. Reflector in painted aluminium, gloss white on the outside and matt white on the inside. Directionable diffuser in transparent mouth-blown glass. Body in matt black. silver anodized or bronze anodized aluminium. Base in nickel-plated metal. Electric cable of useful length 220 cm, with dimmer switch for ON/OFF and adjustment of the light flow between 10-100%. Plug-in power supply with interchangeable plugs.

Are you a professional and your project needs consulting and support?

[BOOK AN APPOINTMENT](#)



### Main specifications

EAN	8059607006672
Mounting	Table floor
Environment	Indoor dry location
Light source type	LED
LED type	LED array
Lamp holder	COB LED
Power (W)	28

### Physical

Colour	Silver
Cord length (mm)	2200
Net weight (kg)	10.74
Package volume (m3)	0.18
IP internal	20

### Download

Mounting instructions	<a href="#">↓ PDF</a>
Mounting instructions	<a href="#">↓ PDF</a>
Spare Parts	<a href="#">↓ PDF</a>

### Photometric Files

LDT / IES	<a href="#">↓ ZIP</a>
-----------	-----------------------

### Technical Drawings

2D	<a href="#">↓ ZIP</a>
3D	<a href="#">↓ ZIP</a>



## Photometric

Lighting type	Indirect
Light distribution	Asymmetric
CCT (K)	2700

## Electrical


Insulation class	III
Frequency (Hz)	50/60
Main voltage (Vac)	100-240/48
Driver	Remote included
Dimmable	Yes
Dimming type	Electronic 48V
Dimming interface	Dimmer Integrated
Plug type	Type G, Type A, Type C
Batteries inside	No
Charging min time	No

## Ecodesign and Energy Labelling

This product contains a light source of energy efficiency class **D**



Replaceable (LED only) light source by a professional



Replaceable control gear by an end-user

## Spare Parts



F6510000  
Taccia transparent diffuser &  
reflector



F6608004  
Anodized silver base



RF00780  
White reflector



RF3320400  
Black plug assembly kit & 48V  
driver



RF6608100  
Jack plug with cable and push  
dimmer